

Ref: QRGD034

PRODUCT:	Dahua Motion Detection
ITEM CODE:	

Introduction

This guide has been formulated to assist with Dahua motion detection.

- 1. Right click and login to recorder. Go to Main Menu > Alarm > Video detection.
- 2. Select the channel number and tick "Enable"

	ALARM							
	Alarm Info	Motion Detection	Video Loss	Video Tamp	pering	PIR		
	Alarm Subscription	Channel	1	- Regio	n	Setting		
	Alarm-in Port	Enable						
>	Video Detection	Cabadula	Catting					
	Exception	Best Besserd	Setting					
	Disarming	Record Channel	1 2 3 4					
		Picture Storage						
		PTZ Linkage	Setting					
		Alarm Tone	None					
			More					

3. Select "Region Setting" to choose what area of screen detects motion.



PureTech Electrical Products Ltd.	Page 1 of 2			
Telephone: +44 (0)2392 488300	Issued By: Technical Dept			
Approved By: Technical Manager	Date: 14/02/2024			





Region – Make up to 4 separate motion detection regions (colour coded)

Sensitivity – How sensitive the motion detection is being triggered.

Threshold – The time/delay between detection.

4. Select "Schedule Setting" to time the motion detection.

		s	etting								×
) 2	4 6	8	10 12	14 16	18 20	22 24	
											Setting
											Setting
											Setting
											Setting
Schedule	Setting										Setting
											Setting
											Setting
			Period 1	 00	in - 2	24 · 00					
			Period 2	00 : 0		24 : 00					
			Dorlod 2								Į
				00 : 0	10 - 2	24 : 00					
			Périod 4	00 : 0	10 - 2	24 : 00					
										ОК	Cancel

5. Set "Post Record" which is the time of recording when motion is detected.

Schedule	Setting	
Post-Record	10	sec.

6. Set which channel number records when motion is detected.



Click Apply once finished.

PureTech Electrical Products Ltd.	Page 2 of 2			
Telephone: +44 (0)2392 488300	Issued By: Technical Dept			
Approved By: Technical Manager	Date: 14/02/2024			