

Ref: QRGD036

PRODUCT:	Dahua – Getting Online + App Setup
ITEM CODE:	

Introduction

This guide has been formulated to assist with getting Dahua recorder online and setting up the app. <u>Getting Online</u>

1. Connect Cat5 cable from LAN port of recorder to LAN port of router OR an Uplink port on a network switch (with router already attached)



2. Using mouse on recorder, right click and log into recorder to access main menu. Browse to Main Menu > Network



3. On the "TCP/IP" screen, click on the Modify pencil (top middle)



4. Turn on DHCP and click Apply/Ok

IC : 9d : 7d : 14 : 23 Э DHCP 168 . 1 . 132		
ic : 9d : 7d : 14 : 23 ● DHCP 168 . 1 . 132		
 9d : 7d : 14 : 23 DHCP 168 . 1 . 132 		
: 9d : 7d : 14 : 23		
О DHCP 168 . 1 . 132		
168 . 1 . 132		

PureTech Electrical Products Ltd.	Page 1 of 5	
Telephone: +44 (0)2392 488300	Issued By: Technical Dept	
Approved By: Technical Manager	Date: 23/05/2024	



5. Make note of the gateway (example below)

Default Gateway	/ 192.1

168.1.253

 Untick/unselect DHCP above the DNS options. Copy the gateway number into the "Preferred DNS" Enter Google DNS into secondary DNS

DHCP				
Preferred DNS	192	168	1	253
Alternate DNS	8	8	8	8

- 7. Click Apply/OK bottom right.
- 8. Select bottom left menu "P2P".

N	lulticast
A	larm Center
R	Register
s	Switch
Р	2P

9. This should be enabled by default (if not select enable). Status should show "Online" in grey



PureTech Electrical Products Ltd.	Page 2 of 5
Telephone: +44 (0)2392 488300	Issued By: Technical Dept
Approved By: Technical Manager	Date: 23/05/2024



App Setup

10. Search for and install DMSS from Play store / Appstore



- 11. Open DMSS and go through intro (you do NOT need to login to the app with an account).
- 12. Press "+" in top right corner, select SN/Scan



Using the scanner, scan the QR code marked "Device SN" on the P2P screen of recorder.



PureTech Electrical Products Ltd.	Page 3 of 5
Telephone: +44 (0)2392 488300	Issued By: Technical Dept
Approved By: Technical Manager	Date: 23/05/2024



13. On following screen press next.



14. Select type of device.

09:40 ٦	0 🗆	R.	♥⊿ 🕯 94%
<	Add D	evice	
Wireless Camera	Wired Camera	PTZ Camera	
DVR/XVR	IVSS		
Other IPC			

15. Enter a name for the device and the login information and press save in top right.

09:40 🦷 🌑 😐	×	♥⊿ 🕯 94%
<	Add Device	Save
Add Mode		P2P
SN	70	
Device Name		
Username		admin
Device Password		Ó

PureTech Electrical Products Ltd.	Page 4 of 5
Telephone: +44 (0)2392 488300	Issued By: Technical Dept
Approved By: Technical Manager	Date: 23/05/2024



16. Press "Done"



17. Cameras will automatically start streaming:



PureTech Electrical Products Ltd.	Page 5 of 5 Issued By: Technical Dept	
Approved By: Technical Manager	Date: 23/05/2024	